

```

/*
C:\fritzbox.cfg
Thu Nov 08 10:26:09 2008 */

vpncfg {
  connections {
    enabled = yes;
    conn_type = conntype_lan;
    name = "FRITZ!Box to FRITZ!Box";
    | Connection name (no account information)

    always_renew = no;
    reject_not_encrypted = no;
    dont_filter_netbios = yes;
    localip = 0.0.0.0;
    local_virtualip = 0.0.0.0;
    remoteip = 0.0.0.0;
    remote_virtualip = 0.0.0.0;
    remotehostname = "otherside.dyndns.org";
    | DynDNS name of the remote site

    localid
    {
      fqdn = "myside.dyndns.org";
    }
    | Own identity IKE phase 1

    remoteid {
      fqdn = "otherside.dyndns.org";
    }
    | Remote site identity IKE phase 1

    mode = phase1_mode_aggressive;
    phase1ss = "all/all/all";
    keytype = connkeytype_pre_shared;
    key = "}be6K8f98a3faf1pwwy)0cRMd9Yf";
    cert_do_server_auth = no;
    use_nat_t = no;
    use_xauth = no;
    use_cfgmode = no;
    | Mode of IKE phase 1 (aggressive)
    | Security policy IKE phase 1
    | Pre-shared key (password)

    phase2localid {
      ipnet {
        ipaddr = 192.168.100.0;
        mask = 255.255.255.0;
      }
    }
    | Own identity IKE phase 2 (IPSEC)
    | Security policy IKE phase 2 (IPSEC)
    | Allowed networks or hosts
    phase2ss = "esp-all-all/ah-none/comp-all/pfs";
    accesslist = "permit ip any 192.168.200.0 255.255.255.0",
      "permit ip any 192.168.10.22 255.255.255.255";
  }
  ike_forward_rules = "udp 0.0.0.0:500 0.0.0.0:500",
    "udp 0.0.0.0:4500 0.0.0.0:4500"; }

// EOF

```